



Asi input board



ASI input board is intended for converting the DVB-ASI transport stream to DVB parallel transport stream and can be used for designing a variety of converters and other digital television equipment.

ASI input board is intended for converting the DVB-ASI transport stream to DVB parallel transport stream and can be used for designing a variety of converters and other digital television equipment. The output transport stream from ASI input board is used as input stream for:

- [DVB-S/S2 modulator](#);
- [DVB-C/T/T2 modulator](#);
- DVB TS-to-IP converter or other compatible format converter.

The input ASI stream can be received in packet or byte modes, 188 or 204 bytes in the packet. The output parallel transport stream is given in byte mode (188 bytes per packet), as the most universal and acceptable for all related modules. In addition, there is LED indication of operating modes on the board for better control.

Parameter	Value
Output Type	DVB ASI, electric
Modes	batch, byte
The number of bytes in the packet	188/204
Defining the type of the input stream	Automatic
Number of outputs	1
Type of output connectors	BNC
Interface output voltage	200 ... 800 mV
Interface output impedance	75 Ohm
Input bitrate	up to 150 Mbps
Output bitrate	up to 150 Mbps
Power	+ 5V +/- 5% VDC
Power consumption	3 W
Dimensions	80x60 mm

Taking into consideration that we (ROKS PrJSC) are developer and system integrator, also do not stop on our technical growth and improvement, know that view of all our devices and equipment including their technical parameters may be different from pictures presented on website and parameters listed on each device webpage.

Note! All details customer has to confirm in advance during ordering and before payment. Those parameters that were not specified and / or were not agreed while ordering will be implemented as basic at the discretion of the manufacturer. Each our customer has 1.5 year warranty and 7 year aftersales support for whole range of our products.