



Lnb-xpdx v1



LNB-XPxx is a PLL LNB with single local oscillator and single output. LO instability ± 25 kHz, Gain 60dB, Noise figure 0.8 dB, Output power P1dB +5 dBm.

The Low Noise Block Down Converter LNB-XPxx designed for gain and transform the RF signals from X-band to the L-band intermediate frequencies. This block has a waterproof case and could be mounted in close proximity to an antenna. LNB's Parameters correspond to the conditions of MVDS/MITRIS TV broadcasting systems according to standard DVB-S/S2 and could be operates up to 25 carriers. LNB-XPxx has input flange PBR84 and could be used with regular RRL or receive antennas.

KEY FEATURES:

- Flange PBR84 input
- Output power is P1dB +5 dBm
- Input frequencies 7.25 - 7.75 GHz
- Output frequencies 950 - 1450 MHz
- Min. gain 60 dB
- Oscillator type PLL
- Operates up to 25 carriers
- Designed for operation in MVDS/MITRIS TV broadcasting systems

Input parameters:	
Input Frequency range	7.25 - 7.75 GHz
Input level, max	-55 dBm
Input VSWR, max	2.2
Input interface	Waveguide WR112, Flange PBR-84
Local Oscillator:	
LO frequency	6.3GHz
LO Phase noise:	
@1 kHz	-75 dBc/Hz
@10 kHz	-85 dBc/Hz
LO instability	± 25 kHz (or ± 10 kHz by order)
Output parameters:	
Output frequency range	950 - 1450
Output Power @P1dB	+5 dBm
Gain, min	60 dB
Output interface	F-type female (or N-type female by order)

Output impedance	75 Ohm (50 Ohm by order)
Output VSWR, max	2.2
Frequency Response:	
Flatness over Full Band	±2 dB
Flatness over 27MHz Band	±0.75 dB
Spurious:	
Noise Figure (@+23°C)	0.8 dB typ
LO leakage, max	-50 dBm
Image rejection, min	45 dBc
Power Supply:	
Input voltage	12 VDC - 24 VDC, nominal 18 VDC
Power consumption, max	3.6 W
Environmental:	
Operating temperature	-40°C to +60°C (-40°F to +140°F)
Storage temperature	-40°C to +80°C (-40°F to +176°F)
Operating humidity	0% - 95%
Mechanical	
Dimensions (W x H x D)	60.4x47x124 mm
Weight	0.45 kg

Taking into consideration that we (ROKS PrJSC) are developer and system integrator, also do not stop on our technical growth and improvement, know that view of all our devices and equipment including their technical parameters may be different from pictures presented on website and parameters listed on each device webpage.

Note! All details customer has to confirm in advance during ordering and before payment. Those parameters that were not specified and / or were not agreed while ordering will be implemented as basic at the discretion of the manufacturer. Each our customer has 1.5 year warranty and 7 year aftersales support for whole range of our products.